


DPA51, DPA71

3-Phase voltage monitoring relay



Benefits

- **Wide voltage range.** Working in systems from 208 to 480 VAC.
- **Output and status LED indication.** For quick troubleshooting.
- **Regenerated voltage detection.** To detect phase loss even while the motor is running.
- **High Compactness.** 17.5 mm (DPA51) and 35.5 mm (DPA71) DIN-rail housing.

Description

DPA51 and DPA71 are 3-phase mains monitoring relays.

They operate on 3P systems, monitoring phase loss and phase sequence.

Power supply provided by the monitored mains.

For mounting on DIN-rail.

Main features


- Monitoring 3-phase mains with 3 wires (3P).
- Detection of the correct phase sequence and phase loss.
- Changeover relay output.

Order code

Mounting	Power supply	Component name/part number
DIN-rail	208 to 240 V AC	DPA71DM23
	208 to 480 V AC	DPA51CM44
	380 to 480 V AC	DPA71DM48



Structure



Element	Component	Function
A	Input terminals	Connection of the line voltages
B	Information LEDs	Yellow for relay output status Green for device ON
C	Output terminals	SPDT relay output (DPA51) DPDT relay output (DPA71)

Features

Power supply

Power supply		Supplied by measured phases (L2, L3)
Overvoltage category		III (IEC 60664)
Voltage range	DPA71DM23	208 to 240 V _{L-L} AC $\pm$ 15% (177 to 276 V)
	DPA51CM44	208 to 480 V _{L-L} AC $\pm$ 15% (177 to 552 V)
	DPA71DM48	380 to 480 V _{L-L} AC $\pm$ 15% (323 to 552 V)
Frequency range		50 to 60 Hz $\pm$ 10% sinusoidal waveform
Consumption	DPA71DM23	< 6 VA
	DPA51CM44	< 13 VA
	DPA71DM48	< 10 VA

Inputs

Terminals	L1, L2, L3	
Measured variables	Phase sequence	
	Phase loss	
	3P: voltages V_{L12} , V_{L23} , V_{L31}	
Nominal line range	DPA71DM23	208 to 240 V AC $\pm 15\%$ (177 to 276 V AC)
	DPA51CM44	208 to 480 V AC $\pm 15\%$ (177 to 552 V AC)
	DPA71DM48	380 to 480 V AC $\pm 15\%$ (323 to 552 V AC)

Outputs


Terminals	DPA51	11, 12, 14
	DPA71	11, 12, 14, 21, 22, 24
Number of outputs	DPA51	1
	DPA71	2
Type	DPA51	SPDT electromechanical relay with changeover contacts
	DPA71	DPDT electromechanical relay with changeover contacts
Logic	Output de-energised on alarm	
Contact rating	DPA51	I_{th} (AC1): 5 A @ 250 V AC DC12: 5 A @ 24 V DC AC15: 2.5 A @ 250 V AC DC13: 2.5 A @ 24 V DC
	DPA71	AC1: 5 A @ 250 V AC AC15: 3 A @ 250 V AC DC13: 2 A @ 24 V DC
Electrical lifetime	$\geq 50 \times 10^3$ operations (at 5 A, 250 V, $\cos \varphi = 1$)	
Mechanical lifetime	$> 30 \times 10^6$ operations	
Assignment	Associated to all alarm types	

Insulation

Terminals		Basic insulation
Inputs: L1, L2, L3 to output: 11, 12, 14	DPA51	2.5 kVrms, 4 kV impulse 1.2/50 μ s
Inputs: L1, L2, L3 to outputs: 11, 12, 14, 21, 22, 24	DPA71	

General

Material	Polyamide (Nylon) (PA66/6) or Phenylene ether + Polystyrene (PPE-PS)
	Flammability rating: HB according to UL 94
Colour	RAL7035 (light grey)
Dimensions (W x H x D)	DPA51: 17.5 x 81 x 67.2 mm (0.68 x 3.19 x 2.65 in)
	DPA71: 35.5 x 81 x 67.2 mm (1.40 x 3.19 x 2.65 in)
Weight	DPA51: approx. 75 g (2.65 oz)
	DPA71: approx. 150 g (5.29 oz)
Terminals	Cable size from 0.05 to 2.5 mm ² (AWG30 to AWG13), stranded or solid
Tightening torque	Max. 0.8 Nm (7.08 lbin)
Terminal type	Screw terminals



Environmental

Operating temperature	DPA51: -20 to 60 °C (-4 to 140 °F)
	DPA71: -20 to 50 °C (-4 to 122 °F)
Storage temperature	-30 to 80 °C (-22 to 176 °F)
Relative humidity	5 - 95% non condensing
Protection degree	IP20
Pollution degree	2
Operating max altitude	2000 m amsl (6560 ft)
Salinity	Non saline environment
UV resistance	No



Vibration/Shock resistance

Test condition	Test	Level
Tests with unpacked device	Vibration response (IEC60255-21-1)	Class 1
	Vibration endurance (IEC 60255-21-1)	Class 1
	Shock (IEC 60255-21-2)	Class 1
	Bump (IEC 60255-21-2)	Class 1
Tests with packed device	Vibration random (IEC60068-2-64)	Class 1
	Shock (IEC 60255-21-2)	Class 1
	Bump (IEC 60255-21-2)	Class 1

Class 1: monitoring devices for normal use in power plants, substations and industrial plants and for normal transportation conditions.

The packaging type is designed and implemented in such manner that the severity class parameters will not be exceeded during transportation.

Compatibility and conformity

Marking					
Directives		2014/35/EU (LVD - Low voltage) 2014/30/EU (EMC - Electromagnetic compatibility)			
Standards		Insulation coordination: EN 60664-1 Immunity: EN61000-6-2 Emission: EN61000-6-3			
Approvals	DPA51CM44	(UL508)		(GB/T14048.5)	
	DPA71DM23 DPA71DM48	(UL508)			

Operating description

Device configuration

The relay operates when all the phases are present and the phase sequence is correct.

Alarms

- Phase loss and incorrect phase sequence cause immediate output relay de-energisation.

Phase loss alarm	
Input variables	L1-L2, L2-L3 and L3-L1
Alarm setpoint	One phase $\leq 85\%$ of the rated value (regenerated voltage detection)
Restore setpoint	All phases $> 85\%$ of the rated value + Hysteresis
Hysteresis	2% fixed
Delay ON	< 100 ms
Delay OFF	< 300 ms

Phase sequence alarm	
Input variables	Connection L1, L2, L3
Reaction time	≤ 200 ms
Delay ON	< 100 ms
Delay OFF	< 300 ms

Information LEDs

Colour	Status		Description
Green ($\oplus$)	Power supply	ON	Power supply ON
		OFF	Power supply OFF
Yellow ($\sim$)	Relay output	ON	Energised
		OFF	De-energised

Operating diagram






Fig. 1 Total phase loss, phase sequence

Connection diagrams

(*) NOTE: fuses F of 315 mA delayed, if required by local law.



DPA51



DPA71

References

Further reading

Information	Where to find it	QR code
Installation manual	https://carlogavazzi-pss.com/manuals/DPA_PPA_IM_html	
PSS selection tool	https://carlogavazzi-pss.com/	
Quick tips (functions tutorial)	https://www.youtube.com/watch?v=UZ70hsuKX5I&list=PL0m_48YH7f4d2uHTLiLu6m6oER5TF5qKi&index=3&t=68s&pp=iAQB https://www.youtube.com/watch?v=UziJWjG3-k4&list=PL0m_48YH7f4d2uHTLiLu6m6oER5TF5qKi&index=4&t=114s&pp=iAQB https://www.youtube.com/watch?v=ZYLxNEf2Hz4&list=PL0m_48YH7f4d2uHTLiLu6m6oER5TF5qKi&index=5&t=43s&pp=iAQB	



COPYRIGHT ©2025

Content subject to change. Download the PDF: www.gavazziautomation.com